


## AMPOLLETA LED BOLA

### DESCRIPCIÓN TÉCNICA

Voltaje 220-240  
Frecuencia 50/60Hz  
Base E27  
Vida Útil 15.000hrs

Diámetro



A55



A60



A70

Código	Descripción	Potencia	Lúmenes	Equivale	T°CColor	Corriente	Diámetro
203006106	AMP LED BOLA A55 5W LBF #65132 E27 UNILUX (X)	5W	450lm	40W	6500K	0,04A	55mm
203006101	AMP LED BOLA A55 5W LC #65128 E27 UNILUX (X)	5W	405lm	40W	3000K	0,04A	55mm
203006107	AMP LED BOLA A60 11W LBF #65133 E27 UNILUX (X)	11W	1055lm	90W	6500K	0,089A	60mm
203006016	AMP LED BOLA A60 7W LBF #65091 E27 UNILUX (X)	7W	600lm	60W	6500K	0,058A	60mm
203006074	AMP LED BOLA A60 7W LC #65120 E27 UNILUX (X)	7W	540lm	60W	3000K	0,058A	60mm
203006015	AMP LED BOLA A60 9W LBF #65090 E27 UNILUX (X)	9W	800lm	70W	6500K	0,072A	60mm
203006075	AMP LED BOLA A60 9W LC #65121 E27 UNILUX (X)	9W	720lm	70W	3000K	0,072A	60mm
203006104	AMP LED BOLA A70 15W LC #65130 E27 UNILUX (X)	15W	1055lm	120W	3000K	0,12A	70mm
203006109	AMP LED BOLA A70 15W LBF #65135 E27 UNILUX (X)	15W	1350lm	120W	6500K	0,12A	70mm
203006102	PACKX2 AMP LED BOLA A60 11W LC #65139 E27 UNILUX (X)	11W	950lm	90W	3000K	0,089A	60mm